

Available in 5 Models

Pure or Modified Sine Wave

TruePower Plus Series

Heavy Duty Marine, Mobile and Industrial Grade Inverters

ProMar Digital Performance Technology Inside

Our next generation of TruePower Plus Inverters are available in both Modified Sine Wave (MS) and Pure Sine Wave (PS) models. Designed to convert 12 VDC battery power to 115 VAC and automatically pass through AC Inlet power when present. Rich with features including; Innovative dual color digital LCD message center, dual color gauges for AC power output and battery DC input, USB power port, GFCI convenience outlets, DC cable covers, and separate on/off remote. Integrated AC cable strain reliefs and front screw connection terminal blocks allow for quick and easy installation without the need for ring terminals for AC power connections.

Designed with soft start noise filtered technology and x2 surge capability for powering demanding loads. Shock resistant construction with internal conformal coated electronics for protection in harsh environments.

The TruePower Plus PS Series has all the features of our MS series but provides a Pure Sine 115 VAC output for high fidelity audio visual systems, in addition to appliances with hysteresis and variable motor speed controls like washing machines and refrigeration etc.

Innovative dual color digital LCD message center

Modified Sine Wave AC power for primarily resistive loads like coffee makers, toasters, grills, and more

Internal 30 amp AC transfer switch will automatically pass through AC inlet power when present

Built-in safety with overload, over temperature, short circuit and reverse polarity protection

Soft start noise filtered technology with x2 surge capability

Shock resistant and internal conformal coated design

Intuitive user friendly operation

Remote with 9 foot cable and DC cable covers included

Compact and lightweight design



Automatic
30 AMP
AC Pass Through



2 GFCI Outlets



USB Power Port



Pure or Modified
Sine Wave

2

Year Warranty




Intuitive Dual Color Display and LCD Message Center



USB 5 VDC/2.1 Amp Port GFCI Protected Outlets



Integrated AC Power Strain Reliefs with Front Screws



DC Cable Covers Black (-) and Red (+)

Automatic
30 AMP
AC Pass Through



2 GFCI Outlets



USB Power Port



Pure or Modified
Sine Wave

2

Year Warranty

TruePower Plus Display Functions

DC to AC Output Gauge

Indicates percentage of AC power being used versus output rating. Scale turns red when output demand exceeds output rating.

Input Power

Indicates if power is coming from DC (batteries) or AC inlet power.

DC Input Level Gauge

Indicates battery DC voltage level. Scale turns red when battery voltage drops below 11 volts.

System Status

Dual color LCD with full system normal and fault condition messaging (no codes).

Check

Illuminates when a fault condition is present with LCD message.



Convert 12 VDC Battery Power to 115 VAC Household Power

Wattage	Application
35	Smartphone / Tablet
100	Can opener/Coffee grinder
150	32"-55" Flat screen TV
175	Laptop computer
300	Portable ice maker
500	Vacuum
550	Washing machine
600	Blender / Food processor
700	Portable dishwasher
750	Full size fridge and freezer
800	Small coffee maker
900	Toaster
1000	Small microwave
1200	Coffee maker
1500	Electric grill
1800	Toaster oven
2000	Large air conditioner

Model	Wattage Range
TruePower Plus 1000ps	35 - 1000 W
TruePower Plus 1200ms	100 - 1200 W
TruePower Plus 1500ms	150 - 1500 W
TruePower Plus 2000ms	150 - 2000 W
TruePower Plus 2000ps	150 - 2000 W

Modified and Pure Sine Wave inverters are for different applications. Pure Sine Wave inverters can be used anywhere that the Modified Sine Wave inverters are used, as well as additional applications. Use above guide to determine the correct sine wave and wattage for your application. Pure Sine Wave models recommended for items shown in blue. Examples listed above are intended for reference only.

TruePower Plus Remote

On/Off control

Input power source LED indicators

Check fault LED indicator

Remote mounting screws
and 9 ft. cable included



Certified to:

UL STD. 458
CSA STD. C22.2 No. 107.2
FCC Class B



Designed and Constructed to: ABYC A-31



model	part no.	wattage	surge rating	AC waveform	efficiency (optimum)	AC output	internal AC transfer switch	AC crossover time	DC input	inverter off DC amp draw	dimensions	weight
TruePowerPlus 1000PS	07100	1000 W	2000 W	Pure Sine Wave	>90%	115 VAC +/- 10%	30 amps	< 30 ms	11-15 VDC	4 mA	4" x 9.9" x 11.5"	7.3 lbs
TruePowerPlus 1200MS	06120	1200 W	2400 W	Modified Sine Wave	>90%	115 VAC +/- 10%	30 amps	< 30 ms	11-15 VDC	4 mA	4" x 9.9" x 11.5"	7.3 lbs
TruePowerPlus 1500MS	06150	1500 W	3000 W	Modified Sine Wave	>90%	115 VAC +/- 10%	30 amps	< 30 ms	11-15 VDC	4 mA	4" x 9.9" x 11.5"	7.3 lbs
TruePowerPlus 2000MS	06200	2000 W	4000 W	Modified Sine Wave	>90%	115 VAC +/- 10%	30 amps	< 30 ms	11-15 VDC	4 mA	4.5" x 10.6" x 11.5"	9.0 lbs
TruePowerPlus 2000PS	07200	2000 W	4000 W	Pure Sine Wave	>90%	115 VAC +/- 10%	30 amps	< 30 ms	11-15 VDC	4 mA	4.5" x 10.6" x 11.5"	9.0 lbs

specifications subject to change without notice